



Deluxe Kit (HPK016) Contents



HHP 7600 Terminal
#H15022



HHP7600 Power Supply
#H15024



Quad Battery Charger
w/power supply & power cord
#H15041



Stylus 3 Pack
#H16108




HHP7600 Spare Battery
#H16103

VTScE Program
#HS6003



SD Card
#H15039

Screen Protector
(For HHP7600)
#H15034



HHP7600 Hand Strap
#H15038

*These Components are installed
on HHP7600 at Hayton Systems.*



Vehicle Adapter
#H15048



Cordura Pouch
(For 7600)
#H15007



Combo Comm Box w/power supply
#H19500



Phone Cord



Custom USB/Serial Cable
#H15029



Hard Shell Case
#H15501

Initial HHP7600 Terminal Connection Process

NOTE: You should have attended a Verizon Training Session in the use of this data collection kit, and have received all necessary instructions directly from Verizon (including valid user name and password).

- 1) Double tap the VTSync Client icon on the “desktop”.
- 2) Enter your Verizon User name and Password (use the pop up keyboard).
- 3) Tap the keyboard icon in the tray at the bottom of the screen (near the right edge).
- 4) Tap on Hide Input Panel.
- 5) Tap Dial-up Settings.
- 6) Verify the phone number entered is 18664833201. If the number is correct then proceed to step 10. If a different number is shown proceed to step 7.
- 7) Highlight the phone number (drag your stylus across the existing number from right to left).
- 8) Press the **BKSP** key to erase the existing number.
- 9) Using the terminal keypad (not onscreen, but “real keys”) type in the new number: 18664833201
- 10) Press the **Ent** key on the keypad to return to the Settings screen.
- 11) Tap OK in the upper right corner of the display.
- 12) Tap Connect once you are ready to proceed (make sure all physical connections are ready).

If you have any questions, please call us at 1-888-270-3582 or email us at brhayton@haytonsystems.com

